



ES-3208P

## 8 Ports Fast Ethernet Switch



### 200Mbps Full Duplex Transmission

Edimax ES-3208P is a high speed fast Ethernet switch for home and small business. ES-3208P not only complies with IEEE 802.3/802.3u 10/100Mbps Ethernet standard but also supports full duplex transmission. The full duplex feature can double the network throughput on every port. It is used for high speed server or switch-to-switch connections. The maximum throughput of every port can reach up to 200Mbps .

### Supports Wire-speed and Flow Control

The ES-3208P built-in non-blocking and store-and-forward architecture feature your network with full-wire speed connections. It accommodates with flow control for full duplex mode and back pressure for half-duplex mode which ensure reliable data transfer and help to prevent data lost. Use ES-3208P to create a high-speeds network and benefit from it's ultimate performance and reliability.

### Supports Auto-MDI/MDI-X and Auto Sensing

ES-3208P supports PnP (plug and play) installation and auto-MDI/MDI-X function. You can connect ES-3208P with computers or Ethernet devices without any configuration. You also can use either straight-through or cross-over Ethernet cable and combine 10 and 100Mbps devices into ES-3208P. The switch will automatically detect the right cable and speed for your device.

### Power Saving

With new generation power saving mode, ES-3208P can reduce power consumption. It is the best solution for home and small business.

## FEATURES AND TECHNICAL SPECIFICATIONS

HARDWARE INTERFACE	FUNCTIONS	POWER ADAPTER
<ul style="list-style-type: none"> <li>8 x RJ-45 Fast Ethernet LAN Ports</li> <li>LED Indicators: Power, LNK/ACT for LAN</li> <li>Power</li> </ul>	<ul style="list-style-type: none"> <li>Non-Blocking</li> <li>Store-and-Forward architecture</li> <li>Full wire speed filtering</li> <li>Auto-MDI/MDI-X and auto learning</li> <li>Auto-negotiation</li> </ul>	<ul style="list-style-type: none"> <li>DC 9V, 0.5A</li> </ul>
STANDARD	HUMIDITY & TEMPERATURE	MEMORY BUFFER
<ul style="list-style-type: none"> <li>IEEE802.3 and IEEE802.3u</li> <li>IEEE802.3x</li> </ul>	<ul style="list-style-type: none"> <li>10-95% (Non-condensing)</li> <li>0~45 Degree Celsius</li> </ul>	<ul style="list-style-type: none"> <li>448K bits</li> </ul>
MAC Address	DIMENSION	CERTIFICATIONS
<ul style="list-style-type: none"> <li>4K</li> </ul>	<ul style="list-style-type: none"> <li>160 x 82 x 25 mm</li> </ul>	<ul style="list-style-type: none"> <li>CE, FCC</li> </ul>

## NETWORK SETUP DIAGRAM AND RELATED PRODUCTS

### An example to setup ES-3208P:

- Connect the ES-3208P to your Router or cable/xDSL modem.
- Connect a computers to ES-3208P.
- You can also connect Print Server, NAS and IP CAMERA to ES-3208P.

