

[Home](#) > [Products](#) > [Motherboard](#) > [Socket AM3+](#) > [GA-970A-UD3 \(rev. 1.0\)](#)**Product List**

Intel Socket 1366
Intel Socket 1155
Intel Socket 1156
Intel Socket 775
Intel BGA 559

AMD Socket AM3+
AMD Socket AM3
AMD Socket AM2+
AMD Socket AM2
AMD BGA FT1

[>> Other Sockets](#)**GA-970A-UD3 (rev. 1.0)**

AMD 970 + SB950 Chipset

[Print](#) | [Microsite](#)☐ Add to Comparison List**Product Comparison****CPU Support List****Accessory Optional****Downloads****Warranty Service****Technical Support****Social Media****GIGABYTE Channel****Overview****Specification****Downloads****Learn more**

CPU	AM3+ Socket: <ol style="list-style-type: none">Support for AMD AM3+ FX processorsSupport for AMD AM3 Phenom™ II processors / AMD Athlon™ II processors <p>(Please refer "CPU Support List" for more information.)</p>
Hyper Transport Bus	<ol style="list-style-type: none">5200 MT/s
Chipset	<ol style="list-style-type: none">North Bridge: AMD 970South Bridge: AMD SB950
Memory	<ol style="list-style-type: none">4 x 1.5V DDR3 DIMM sockets supporting up to 32 GB of system memory (Note 1)Dual channel memory architectureSupport for DDR3 2000(O.C.)/1866/1600/1333/1066 MHz memory modules (Note 2) <p>(Please refer "Memory Support List" for more information.)</p>
Audio	<ol style="list-style-type: none">Realtek ALC889 codecHigh Definition Audio2/4/5.1/7.1-channelSupport for S/PDIF Out
LAN	<ol style="list-style-type: none">1 x Realtek RTL8111E chip (10/100/1000 Mbit)
Expansion Slots	<ol style="list-style-type: none">1 x PCI Express x16 slot, running at x16 (PCIEX16)1 x PCI Express x16 slot, running at x4 (PCIEX4)3 x PCI Express x1 slots <p>(All PCI Express slots conform to the PCI Express 2.0 standard.)</p> <ol style="list-style-type: none">2 x PCI slots
Storage Interface	South Bridge: <ol style="list-style-type: none">6 x SATA 6Gb/s connectors supporting up to 6 SATA 6Gb/s devicesSupport for RAID 0, RAID 1, RAID5, RAID 10 and JBOD
USB	South Bridge: <ol style="list-style-type: none">Up to 14 USB 2.0/1.1 ports (8 ports on the back panel, 6 ports available through the internal USB headers) <p>2 x Etron EJ168 chips:</p> <ol style="list-style-type: none">Up to 4 USB 3.0/2.0 ports (2 ports on the back panel, 2 ports available through the internal USB header)

**Contact Us • GIGABYTE
Channel • Site Map • Term of
Use • Privacy • RSS**

All intellectual property rights, including without limitation to copyright and trademark of this work and its derivative works are the property of, or are licensed to,
GIGA-BYTE TECHNOLOGY CO., LTD. Any unauthorized use is strictly prohibited.

	VIA VT6308 chip:
IEEE 1394	1. Up to 2 IEEE 1394a ports (1 port on the back panel, 1 port available through the internal IEEE 1394a header)
Internal I/O Connectors	1. 1 x 24-pin ATX main power connector 2. 1 x 8-pin ATX 12V power connector 3. 6 x SATA 6Gb/s connectors 4. 1 x CPU fan header 5. 2 x system fan headers 6. 1 x power fan header 7. 1 x front panel header 8. 1 x front panel audio header 9. 1 x S/PDIF Out header 10. 3 x USB 2.0/1.1 headers 11. 1 x USB 3.0/2.0 header 12. 1 x IEEE 1394a header 13. 1 x Trusted Platform Module (TPM) header 14. 1 x serial port header 15. 1 x clearing CMOS jumper
Back Panel Connectors	1. 1 x PS/2 keyboard/mouse port 2. 1 x optical S/PDIF Out connector 3. 1 x IEEE 1394 port 4. 8 x USB 2.0/1.1 ports 5. 2 x USB 3.0/2.0 ports 6. 1 x RJ-45 port 7. 6 x audio jacks (Center/Subwoofer Speaker Out/Rear Speaker Out/Side Speaker Out/Line In/Line Out/Microphone)
I/O Controller	1. ITE IT8720 chip
H/W Monitoring	1. System voltage detection 2. CPU/System temperature detection 3. CPU/System/Power fan speed detection 4. CPU overheating warning 5. CPU/System/Power fan fail warning 6. CPU/System fan speed control (Note 3)
BIOS	1. 2 x 32 Mbit flash 2. Use of licensed AWARD BIOS 3. Support for DualBIOS™ 4. PnP 1.0a, DMI 2.0, SM BIOS 2.4, ACPI 1.0b
Unique Features	1. Support for @BIOS 2. Support for Q-Flash 3. Support for Xpress BIOS Rescue 4. Support for Download Center 5. Support for Xpress Install 6. Support for Xpress Recovery2 7. Support for EasyTune (Note 4) 8. Support for Easy Energy Saver 9. Support for Smart Recovery 10. Support for Auto Green 11. Support for ON/OFF Charge 12. Support for Cloud OC 13. Support for 3TB+ Unlock 14. Support for Q-Share
Bundle Software	1. Norton Internet Security (OEM version)
Operating System	1. Support for Microsoft Windows 7/ Vista/ XP
Form Factor	1. ATX Form Factor; 30.5cm x 24.4cm

Note	<p>(Note 1) Due to Windows 32-bit operating system limitation, when more than 4 GB of physical memory is installed, the actual memory size displayed will be less than 4 GB.</p> <p>(Note 2) To support a DDR3 1866 MHz (and above) memory, you must install an AMD AM3+ CPU first.</p> <p>(Note 3) Whether the CPU/system fan speed control function is supported will depend on the CPU/system cooler you install.</p> <p>(Note 4) Available functions in EasyTune may differ by motherboard model.</p>
Remark	<ol style="list-style-type: none">1. Due to different Linux support condition provided by chipset vendors, please download Linux driver from chipset vendors' website or 3rd party website.2. Most hardware/software vendors no longer offer support for Win9X/ME/2000/XP SP1/SP2. If drivers are available from the vendors, we will update them on the GIGABYTE website.

* The entire materials provided herein are for reference only. GIGABYTE reserves the right to modify or revise the content at anytime without prior notice.

* Advertised performance is based on maximum theoretical interface values from respective Chipset vendors or organization who defined the interface specification. Actual performance may vary by system configuration.

* All trademarks and logos are the properties of their respective holders.

* Due to standard PC architecture, a certain amount of memory is reserved for system usage and therefore the actual memory size is less than the stated amount.