



IC-1510/IC-1510Wg

EDIMAX

Fast Ethernet / Wireless 802.11b/g Internet Camera

Easy Setup

No need to worry about complex network setup procedures. The install wizard can provide easy setup procedure to use camera.

Simultaneous Viewing

This Internet Camera allows multiple users login to view live video simultaneously. The advanced video compression produces a high-quality, high-frame rate, VGA, QVGA video stream.

Standard Image Format

The Internet Camera delivers complete, high-quality pictures in standard JPEG format, which can be viewed using any standard browser.

Support Windows-based and Web-based Monitoring Utility

These tools allow users to access the Internet Camera from a remote site via Intranet or Internet. They also provide users to make function configuration including image monitoring, recording images to a hard drive, viewing up to 4 cameras on one screen, snapshots and so on.

Supports DDNS & UPnP

The camera also supports UPnP and DDNS. DDNS allows the camera to use an easier to remember naming format rather than an IP address. UPnP will allow users of Windows XP to access the camera with the click of a mouse without knowing IP address of the camera.

FEATURES AND TECHNICAL SPECIFICATIONS

INTERFACE	MANAGEMENT	POWER ADAPTER
<ul style="list-style-type: none"> 1 Ethernet (RJ-45) Port 1 Power Jack 1 Reset Button 1 External Detachable Antenna (IC-1510Wg) 	<ul style="list-style-type: none"> Provides Admin Utility, Camera Viewer & Web browser management Firmware upgradeable 	<ul style="list-style-type: none"> DC 12V, 0.4A
LED	HARDWARE	HUMIDITY
<ul style="list-style-type: none"> LAN WLAN Power 	<ul style="list-style-type: none"> 0.3M Pixels CMOS Sensor Manual Focus, F= 2.8mm 2 MB Flash 16 MB SDRAM 	<ul style="list-style-type: none"> 10-90% (Non-condensing)

FUNCTIONS	DIMENSION & TEMPERATURE	CERTIFICATIONS
<ul style="list-style-type: none"> Motion-JPEG Image Video Digital 24-bit Color Provides Manual Focus Lens Supports Up to 20 fps Video Frame Rate High Speed Hardware-Based Image Compression Includes easy-to-use Viewer & Recorder utility Provide Admin utility, Camera Viewer & WEB browser Management Supports Wireless 802.11b/g configuration View multiple cameras simultaneously - Up to 4 at a time Supports four additional user accounts for viewing camera Manual/Schedule/Cycle Record, Video Playback/Forward/Pause/Stop Supports Motion-Detection Firmware Upgradeable 	<ul style="list-style-type: none"> 114 X 79 X 50 mm 0~45 °C 	<ul style="list-style-type: none"> CE, FCC, C-Tick

SYSTEM REQUIREMENTS

- OS System: Windows 98 , ME , 2000, XP + SP2, Server 2003
- IE Version: 6.0.29 + SP2 or above
- CPU: Intel Pentium III 750MHz above or Intel Celeron 1GHz above
- Memory Size: 128MB (256MB recommended)
- DirectX 9.0 or above
- VGA card with fully DirectX 9.0 supported.
- VGA Card Resolution: 800 x 600 or above

NETWORK SETUP DIAGRAM AND RELATED PRODUCTS

An example of how the IC-1510Wg can be setup:

- Connect the IC-1510Wg to PC by Ethernet (RJ45) LAN port.
- Install the Admin Utility into your PC and set up the IC-1510Wg IP subnet as same as Broadband Router's.
- Configure IC-1510Wg with Broadband Router via wireless connection.
- All computers in the local network can now view the IC-1510Wg.
- To view the IC-1510Wg via the Internet, open the http and video ports in the router. Then, you can watch live video from anywhere in the world.

