



EW-7622UMn

300Mbps Wireless 802.11b/g/n USB Adapter



Simply plug your new Edimax EW-7622UMn USB adapter into your computer's USB port, and enjoy high-speed wireless network access. This mini wireless USB adapter provides a simple and easy way to add or upgrade the wireless connectivity of your desktop, laptop or notebook computer. You can enjoy high data transfer rate at up to 300Mbps when your Edimax EW-7622UMn USB adapter is connected with wireless 802.11n-compatible devices.

Wireless 802.11n Standard (data rates up to 300Mbps)

Edimax EW-7622UMn provides extended wireless coverage and higher data transfer rate, latest wireless technology extends wireless coverage by 5 times, and eliminates wireless dead spots. EW-7622UMn USB adapter is compatible with IEEE802.11b/g/n wireless standards, and is capable to transfer data at up to 300Mbps when connected with 802.11n wireless devices. The wireless technology used by Edimax EW-7622UMn USB adapter also makes wireless signal travel for longer distance, and provides more reliable wireless connections when comparing with traditional IEEE802.11b/g wireless network.

Features Hardware WPS (Wi-Fi Protected Setup) button

Wi-Fi Protected Setup (WPS) is a new technology designed to establish a secure wireless network in a fast and easy way. If the wireless device you wish to connect supports WPS, Edimax EW-7622UMn USB adapter will establish a secure, encrypted WPA data connection with it. All you need to do is only a simple key press. Edimax EW-7622UMn USB adapter supports both hardware (push button) and software (web page setup) WPS.

Features Multi-language EZmax Setup Wizard

Edimax EW-7622UMn includes an EZmax setup wizard – a setup application available in 16 languages, which will assist you to connect your new EW-7622UMn USB adapter with wireless network in no time.


Compact, Portable Design

Edimax EW-7622UMn wireless USB adapter is compact and portable, makes it become the first choice for mobile users.

USB Stand Improves Wireless Performance

When using Edimax EW-7622UMn wireless USB adapter with the USB stand included in product package, it will provide better wireless performance at no extra cost.

* The EZMax Setup CD Wizard only supports the Edimax wireless Series.



FEATURES AND TECHNICAL SPECIFICATIONS

- Complies with wireless 802.11b/g/n standards with data rate up to 300Mbps
- Extends wireless coverage for 5 times
- Includes multi-language EZmax setup wizard.
- Supports 64/128-bit WEP, WPA, WPA2, WPS and IEEE802.1x encryption for wireless security
- Supports WMM

HARDWARE INTERFACE	STANDARD	FREQUENCY BAND
<ul style="list-style-type: none"> 1 USB 1.0/2.0 Type A Hardware WPS button Internal Printed Antennas 	<ul style="list-style-type: none"> IEEE802.11b, 802.11g, 802.11n 	<ul style="list-style-type: none"> 2.4000~2.4835GHz (Industrial Scientific Medical Band)

DATA RATE	INSTALLATION	LED
<ul style="list-style-type: none"> 11b: 1/2/5.5/11Mbps 11g: 6/9/12/24/36/48/54Mbps 11n (20MHz): MCS0-15 (up to 144Mbps) 11n (40MHz): MCS0-15 (up to 300Mbps) 	<ul style="list-style-type: none"> Multi-language EZmax Setup Wizard 	<ul style="list-style-type: none"> Link/Activity

SECURITY	DIMENSION	HUMIDITY & TEMPERATURE
<ul style="list-style-type: none"> WEP 64/128, WPA, WPA2 and IEEE802.1x Supports WMM Hardware and Software WPS configuration 	<ul style="list-style-type: none"> 61(H) x 20.5(W) x 10(D) mm 	<ul style="list-style-type: none"> Max. 95% (Non Condensing) 32~104°F (0~40°C)

SYSTEM REQUIREMENTS	OUTPUT POWER	CERTIFICATIONS
<ul style="list-style-type: none"> Windows 2000/XP/Vista/7, Mac 10.4.x or above and Linux 	<ul style="list-style-type: none"> 11n: 12dBm±1dBm, 11g: 12dBm±1dBm, 11b: 17dBm±1dBm 	<ul style="list-style-type: none"> CE, FCC, WiFi

NETWORK SETUP DIAGRAM AND RELATED PRODUCTS

Example Edimax EW-7622UMn setup:

- Plug the mini wireless adapter into your computer.
- Setup the wireless connection by running EZmax wizard.
- Connect to 802.11b/g/n wireless access point or wireless broadband router.

